

Reference for Simeon soundfield FM models

	Simeon 300WU	Simeon 366WU	Simeon 466WU	Simeon 801 Omni	Simeon 202 Omni	Simeon 966 Omni Simeon 966 Mini
Power adapter model for receiver	PA1010-120DUB	MW48-150-1000	STD-1502	SimD12-25A	SimD12-25A	STD-1638
Power adapter for transmitter charging stand HDC-202	AD41-1200500DU or PA1010-120DUB	AD41-1200500DU or PA1010-120DUB	AD41-1200500DU or PA1010-120DUB	NOT APPLICABLE	NOT APPLICABLE	AD41-1200500DU or PA1010-120DUB
Transmitter model/s	8LT (UHF)	8LT (UHF)	8LT (UHF) 801TS (UHF)	8LT (UHF)	2LT (VHF Fixed freq.) 269T (VHF Fixed freq.)	8LT (UHF) 801TS (UHF)
Number of channels	16	16 (Plus Auto-Tracking)	16 (Plus Auto-Tracking)	16	10 Pairs (Fixed VHF)	16
Transmitter charging method	Charger HDC-202 (Charger only - Leave switched ON to charge)	Charger HDC-202 (Charger only - Leave switched ON to charge)	Charger HDC-202 (Charger only - Leave switched ON to charge)	Receiver/charger 801RC (Receiver must be turned OFF to activate the charging pocket)	Receiver/charger 202RC (Receiver must be turned OFF to activate the charging pockets)	Charger HDC-202 (Charger only - Leave switched ON to charge) Charger HDC-202 may also be powered from DC output of 966R
Auxiliary output to connect to personal FM transmitters	AUX	REC OUT	AUX /REC	AF	AF.A & AF.B	AUX OUT
Batteries	Transmitter: NiMH AA rechargeable x 2. Receiver/speaker: NiMH AA rechargeable x 6.	Transmitter: NiMH AA rechargeable x 2. Receiver/speaker: BAT.366-12 x 1.	Transmitters: NiMH AA rechargeable x 2. Receiver/speaker: BAT.466-12 x 1.	Transmitter: NiMH AA rechargeable x 2. No receiver battery (DC power adapter only)	Transmitters: NiMH AA rechargeable x 2. No receiver battery (DC power adapter only)	Transmitters: NiMH AA rechargeable x 2. No receiver battery (DC power adapter only)
Antenna type	Built-in Antenna	External: #765 or #840	External: #765 or #840	External: #765 or #840	External: VHF	External: #765 or #840
Omnipanel cable and connector type	NOT APPLICABLE	NOT APPLICABLE	NOT APPLICABLE	Uses EN-3 speaker cable – 3 metres	Uses EN-3 speaker cable – 3 metres	Uses Speakon speaker cable – 5 metres

Supportive Hearing Systems
www.fmhearing.com

Customer support: 1-(800) 732-8804
customerservice@fmhearing.com